

# UT106



## UTSTARCOM MULTI-LANGUAGE HANDSET

VERSATILE AND LEADING-EDGE PHONE THAT SUPPORTS MULTIPLE LANGUAGES

### KEY FEATURES

- MULTI-LANGUAGE SUPPORT (SPANISH / FRENCH / PORTUGUESE / ENGLISH)
- SMS GROUP SENDING
- MUSIC KEY TONE
- 4 POLYPHONIC MELODIES
- ONE KEY MUTE MODE
- SCHEME DIY, STANDBY PICTURE REFRESH PERIODICALLY
- eZi INTELLIGENT ENTRY
- HARDWARE ANTI-CLONE

### TECHNICAL PROFILE

Subject	Specifications
Dimensions (HxWxD)	99.5 x 42 x 17.5mm (Approx.)
Weight	70g (Approx.)
Battery	Li-ion DC 3.6V 480mAh
Charger	Input 100 ~ 240 VAC 50 ~ 60Hz Output 5.2V DC 320mA
Talk Time	Up to 4 hours
Charging Time	Up to 5 hours (Approx.)
Standby time	50 ~ 200 hours

### SYSTEM STANDARDS

COMMUNICATION SYSTEM	TDMA/TDD SYSTEM
FREQUENCY BAND	1.9GHz (1880MHz~1920MHz)
TRANSMISSION OUTPUT	10mW at antenna connector

### ADDITIONAL FEATURES

- SMS
- One Key Mute Incoming Call
- Support phonebook down load via Data cable (optional)
- Support multiple system parameters
- Support power on registration/ power off notification
- Intelligent Search in Phonebook
- 35 Ring tones / Melodies
- Wall Paper and Power On/Off Animation
- Call Logs (20 Incoming/20 Outgoing/20 Missed)
- SMS Records (Inbox 100/Outbox 100/Draft 10)
- 200 Phonebook Records
- 4 Profiles (Standard/Mute/Outdoor/User defined)
- Profile and common setting shortcut
- Speed Dial function
- Security password preset
- Power On/Off Animation
- Time/Talking Time Display & Alarm (Snooze Type)
- Call holding/Call Waiting/Call Diverting / Conference Call
- Handset Lock
- Calculator/Memo/Calendar
- Games

### CERTIFICATION

FCC ID: O6Y-UT106

Products are certified in markets specifically listed on this spec.

#### UTStarcom, Inc. USA

1275 Harbor Bay Parkway  
Alameda, CA 94502, USA  
Tel. 510-864-8800  
Fax. 510-864-8802

Copyright © 2004 UTStarcom, Inc. All Rights Reserved. UTStarcom and the UTStarcom logo are the registered trademarks of UTStarcom, Inc. and its subsidiaries. UTStarcom reserves the right to modify the specifications without prior notice.